



Center for the **A**dvancement of **N**atural
Discoveries using **L**ight **E**mission


RF Gun Design and Performance for AREAL Linac

Andranik Tsakanian


CANDLE, Yerevan, Armenia

CANDLE
26 June 2012


Layout of S-band Photocathode RF Gun (DESY Design)



Resonant TM010 mode



Cavity parameters for TM 010 resonant mode	
Frequency - f [GHz]	2.99646
Unloaded quality factor - Q_0	15292.34
Shunt impedance - R [M Ω]	4.234953
R/Q_0 [Ω]	276.933
External quality factor - Q_e	15434.52
Loaded quality factor - $Q = (1/Q_0 + 1/Q_e)^{-1}$	7681.55
Coupling factor - $\beta = Q_0/Q_e$	0.99
Natural filling time (loaded/unloaded) - $\tau = Q/(2\pi f)$ [μ s]	0.408



Expecting parameters for $6MW$ input power

AREAL design parameters (single bunch mode)	
Bunch charge	10 – 200 pC
Bunch length	5 – 10 ps
Repetition rate	1 Hz



Expected cavity parameters for $P=6MW$ input power	
Maximum acc. voltage $V_{acc} = \sqrt{P \cdot R / Q_0 \cdot Q_e}$	5.07 MV
Maximum acc. E_z field	117.3 MV/m
Maximum beam power $P_b = I_b \cdot V_{acc}$	~ 1 mW

Expecting parameters for 6MW input power

AREAL design parameters (single bunch mode)	
Bunch charge	10 – 200 pC
Bunch length	5 – 10 ps
Repetition rate	1 Hz



Expected cavity parameters for $P=6MW$ input power	
Maximum acc. voltage $V_{acc} = \sqrt{P \cdot R / Q_0 \cdot Q_e}$	5.07 MV
Maximum acc. E_z field	117.3 MV/m
Maximum beam power $P_b = I_b \cdot V_{acc}$	~ 1 mW

Beam induced voltage on TM 010 accelerating mode (Wake fields)

Wake function $\rightarrow w_n(s) = 2K_n \cos\left(\frac{2\pi f_n}{c}s\right) e^{-\frac{s}{c\tau_n}}$


$$K_{010} = \frac{2\pi f_{010}}{4} \left(\frac{R_{010}}{Q_{010}} \right) = 1.315 \frac{V}{pC}$$

Wake potential $\rightarrow W_n(s) = \int_{-\infty}^s w_n(s-s') \cdot \rho(s') ds'$

Beam loading

Maximum induced voltage by 200pC bunch
and rectang.-charge distribution ($L=3$ mm)

$$V_{b,induced} = 0.525 kV$$



Further Steps

- Coupler performance
- Coupler optimization for solenoid space

Further Steps

- Coupler performance
- Coupler optimization for solenoid space

Thank You for Attention!

